



## KEY SYSTEM FEATURES

- » Linux Operating System
- » 3 Tier Architecture
- » Encrypted Communication
- » Remote System Monitoring
- » Remote Programmability
- » Remote Arming
- » Remote Power Monitoring
- » Versatile Reporting Features
- » Send Text Messages
- » Audio Broadcast
- » Easy Programmability

The AP1002 series panel has been specifically designed for condominium and senior residences. It allows remote site monitoring as well as onsite monitoring with the building administrative area.

## AP 1002 SPECIFICATIONS

**Input Power:** 50mA - 75mA (18AWG)

**Operating Temp:** 0°C ~ 50°C

**Status LEDs:** Green, Red & Amber

**Display:** 4x20 LCD with backlight

**Dev-Com:** 2 Wire PESI Net (24AWG)

**Loop Types:** NC, NO, NC-1R, NO-1R,  
NC-2R, NO-2R, NC-NO-1R

**Loop Persistency:** 300ms to 60s

**Output:** 2 Electronic relay output

**Back-box:** 2 or 3 gang

**Color:** ABS Plastic in Off White

**Dimension:** 17 x 12 x 3 cm  
(Approx. W x H x D)

- » Aesthetically designed panel that blends with any background
- » Specially designed for condominium and senior residences
- » Big character 4x20 LCD for better user accessibility
- » 3 LEDs to display Panel status from far distance
- » 27 button, tactile operational back lit keypad with the Emergency key always illuminated
- » Single press Emergency, Panic, Medic, Message, Check-In, Audio & Valet request keys
- » 3 Arming modes (Instant, Stay & Away)
- » 10 Fully configurable zones (Entry / Exit, Door/Window, Motion, Fire, Gas, Other-Always & Other-Armed)
- » All zones are monitored for Trouble & Fault Conditions
- » 10 Traceable User Codes, User Codes are custom programmable for each suite
- » 1 Custom programmable Master / Duress code
- » 1 Factory assigned Service code
- » User selectable door chimes
- » Trouble/Fault Zones bypassable by Master User
- » Send Custom Text Message
- » Hands Free Audio communication to the Guard Desk
- » Supervised for Tamper conditions
- » Built in Energy efficient switching power module to conserve power
- » Control Door/Elevator access modes
- » Enable / Disable Party Mode
- » Enable / Disable Privacy Modes
- » Check-In feature for Senior Homes/Hospitals. Check-In intervals are user selectable
- » User selectable Audio Level
- » User selectable LCD contrast Level
- » Fully functional without the Controller / Computer
- » Can be configured to control another slave panel (Master / Slave configuration).

A Product of North America